

Courtesy Delco-Remy Corp., Anderson, Ind.

GENERATOR—942-A—Third Brush Regulation—No Thermostat.

Rotation—Clockwise, viewed from drive end.

Field Reading—5 amps., 6 volts.

Relay Cut-in—660 Generator R. P. M.

Output at 850 R.P.M.—7 amps., 7.0-7.3 volts.

Max. Cold Output—17 amps., 8.05 volts—1600 R.P.M.

Max. Hot Output—13 amps., 7.85 volts—1850 R.P.M.

Brush Tension—16-18 oz.

TEST DATA

STARTING MOTOR—712-E.

Rotation—Clockwise, viewed from drive end.

No Load—5 volts, 65 amperes, approx. 5000 R.P.M.

Lock Torque—11 ft. lbs., 3.6 volts, 450 amps.

Brush Tension—24-28 oz.

